

IP67 Roof Mount Camera with Night Vision User Manual



EchoMaster.com

EchoMaster is a Power Brand of AAMP Global



email - support@aampglobal.com (Europe) email - technical.eu@aampglobal.com (Europe)

> 15500 Lightwave Drive, Suite 202 Clearwater, Florida 33760



Introduction

Thank you for purchasing your EchoMaster Pro automotive camera.

The following part numbers are supported:

- ► PCAM-RM1-P
- ► PCAM-RM1-N

EchoMaster cameras are designed to improve safety during driving by providing high quality images of surrounding areas and obstacles in the vicinity of the vehicle. They will also improve vehicle maneuvering capability by displaying blind spots not normally visible to the driver.

Please ensure you read and understand all aspects of this manual before fitting or using your EchoMaster Camera. Choose a suitable mounting place dependent on the application. Ensure that there are no wiring harnesses or hoses/pipes located behind this panel before drilling.


Key Features

- ▶ 1/4" CCD Sensor
- Operates at 0 LUX
- ▶ 9 IR LEDs
- ▶ IP67 Rated
- ▶ 120 Degree Viewing Angle

Box Contents

- Camera
- Gasket
- Manual
- Mounting Hardware

Dimensions





Specifications

| | PCAM-RM1-P I PCAM-RM1-N |
|---------------------|----------------------------|
| Sensor | 1/4" CCD |
| LEDs | 10 |
| Illumination | 0 LUX |
| Viewing Angle | 120 degrees |
| Mirror Image | NO |
| Normal Image | YES |
| Water/Debris-Proof | IP67 |
| Audio | NO |
| Power Supply | 12V DC |
| Current | <120mA |
| Working Temperature | -20°C - +70°C |
| Dimensions (mm) | D (205) x W (129) x H (59) |
| System | PAL NTSC |
| TV Lines | 420 420 |
| Resolution (HxV) | 680 x 512 768 x 494 |

Wiring Diagram & Pin Out

